Solstar LED















Solstar LED is a high performance range of LED downlights designed with both new build and retrofit projects in mind. Many new LED downlights have reduced the housing diameter to suit the LED source, however, the traditional dimensions of the two sizes in this range are ideal for retrofit/upgrade situations due to the large cut out diameter left by the existing product.

Available in four light output versions, all are backed up by a 3 hour maintained emergency option. Solstar LED is highly versatile and suits most internal applications. The die-cast aluminium front bezel can be substituted for an ever popular haloglass attachment by retrofitting in a simple twist and lock motion.

- Energy saving of 75% when compared to already low energy fluorescent models
- Twist and lock attachment for ease of installation and clean aesthetics
- Cut out diameter designed to match most compact fluorescent types, which makes Solstar LED an ideal upgrade product
- Highly versatile with a wide range of lumen outputs and 3 hour maintained emergency versions to suit many applications
- DALI dimmable option increases potential energy savings and provides additional user comfort and control

Lamp and Control Gear Options

- High performance LED array and LED driver system
- 4000K, Ra +80

Materials

- Housing die cast aluminium
- · Bezel die cast aluminium in white finish
- Bezel optic diffused white finish, opal polycarbonate (TPa rated)

Installation Notes

- The luminaire head is IP44 rated, the remote control gear is IP20 rated
- The integrated ceiling clamp screws are accessed during installation by removing the twist and lock bezel
- The ceiling clamps suit ceiling depths of up to 45mm large, 30mm small
- The haloglass accessory attachment is retained with a twist and lock action and replaces the standard bezel
- Allow a minimum of 100mm clearance around the downlight and 35mm above to allow adequate air flow
- Haloglass accessories reduce the lumen output by approx 6.3%. Photometric data files are available on request or via Relux and Dialux

Options


- Haloglass accessory ordered separately
- Integrated 3hr maintained emergency functionality

Specification

To specify state: Recessed LED downlight with twist and lock die-cast aluminium bezel. HF/DALI control gear with plug and socket connection as Eaton's Solstar LED range, part no. _____

Photometric Data


Solstar LED Small Cat. No. SLD100KZ



| Utilisation factors / TM5 | | | | | | | | | | | |
|---------------------------|----|----|------------|-----|------|-----|-----|-----|-----|-----|-----|
| Reflectances | | | Room Index | | | | | | | | |
| C | W | F | 0.75 | 1.0 | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | 5.0 |
| 70 | 50 | 20 | 67 | 77 | 83 | 88 | 94 | 98 | 101 | 104 | 107 |
| 70 | 30 | 20 | 61 | 71 | 77 | 82 | 89 | 94 | 97 | 101 | 104 |
| _70 | 10 | 20 | 56 | 66 | 73 | 78 | 85 | 90 | 94 | 98 | 102 |
| 50 | 50 | 20 | 66 | 75 | 81 | 85 | 91 | 95 | 97 | 101 | 103 |
| 50 | 30 | 20 | 60 | 69 | 76 | 81 | 87 | 91 | 94 | 98 | 100 |
| _50 | 10 | 20 | 55 | 65 | 72 | 77 | 84 | 88 | 91 | 96 | 98 |
| 30 | 50 | 20 | 64 | 73 | 79 | 83 | 88 | 92 | 94 | 97 | 99 |
| 30 | 30 | 20 | 59 | 68 | 75 | 79 | 85 | 89 | 91 | 95 | 97 |
| 30 | 10 | 20 | 55 | 65 | 71 | 76 | 82 | 86 | 89 | 93 | 95 |
| 0 | 0 | 0 | 53 | 62 | 69 | 73 | 79 | 83 | 85 | 89 | 91 |
| BZ-class | | 2 | 2 | 2 | 2 | 2 | 2 | 2 | 2 | 2 | |

See page 458 for design guide


Solstar LED Large Cat. No. SLD260KZ




| Utilisation factors / TM5 | | | | | | | | | | | |
|---------------------------|-------|----|------------|-----|------|-----|-----|-----|-----|-----|-----|
| Reflectances | | | Room Index | | | | | | | | |
| С | W | F | 0.75 | 1.0 | 1.25 | 1.5 | 2.0 | 2.5 | 3.0 | 4.0 | 5.0 |
| 70 | 50 | 20 | 66 | 76 | 83 | 87 | 93 | 98 | 100 | 104 | 106 |
| 70 | 30 | 20 | 59 | 69 | 76 | 81 | 88 | 93 | 96 | 101 | 103 |
| 70 | 10 | 20 | 54 | 65 | 72 | 77 | 84 | 89 | 93 | 98 | 101 |
| 50 | 50 | 20 | 65 | 74 | 80 | 85 | 90 | 94 | 97 | 100 | 102 |
| 50 | 30 | 20 | 59 | 68 | 75 | 80 | 86 | 90 | 93 | 97 | 100 |
| 50 | 10 | 20 | 54 | 64 | 71 | 76 | 86 | 87 | 91 | 95 | 98 |
| 30 | 50 | 20 | 63 | 72 | 78 | 82 | 88 | 91 | 93 | 97 | 98 |
| 30 | 30 | 20 | 58 | 67 | 74 | 78 | 84 | 88 | 91 | 94 | 97 |
| 30 | 10 | 20 | 54 | 63 | 70 | 75 | 81 | 85 | 88 | 92 | 95 |
| 0 | 0 | 0 | 52 | 61 | 67 | 72 | 78 | 82 | 84 | 88 | 90 |
| В | Z-cla | ss | 2 | 3 | 3 | 3 | 3 | 2 | 3 | 3 | 3 |

See page 458 for design guide

Dimensions







Catalogue Numbers

| Lumen Output | Wattage (W) | Llm/cW | Cat No | Weight (kg) | Emergency Cat No | Weight (kg) |
|-------------------|-------------|--------|------------|-------------|------------------|-------------|
| Solstar LED Small | | | | | | |
| 966lm | 10 | 96.6 | SLD100KZ | 0.6 | ERSLD100KZ | 1.2 |
| 1433lm | 15 | 95.5 | SLD145KZ | 1.2 | ERSLD145KZ | 1.9 |
| Small Haloglass | | | SLDSHGLASS | 0.24 | | |
| Solstar LED Large | | | | | | |
| 1921lm | 18 | 106.7 | SLD195KZ | 1.2 | ERSLD195KZ | 1.9 |
| 2608lm | 27 | 96.6 | SLD260KZ | 1.2 | ERSLD260KZ | 1.9 |
| Large Haloglass | | | SLDLHGLASS | 0.54 | | |

Note: Standard versions are Class II double insulated Emergency versions are Class I and must be earthed

For DALI dimmable options, replace the Z with DD, e.g. SLD260KZ becomes SLD260DD